



Deutsche Akkreditierungsstelle

Annex to the Accreditation Certificate D-K-17805-01-00 according to DIN EN ISO/IEC 17025:2018

Valid from: **06.12.2022**

Date of issue: 06.12.2022

Holder of accreditation certificate:

Rosenberger Hochfrequenztechnik GmbH & Co. KG
HF-Kalibrierlabor
Hauptstraße 1, 83413 Fridolfing

The calibration laboratory meets the minimal requirements of DIN EN ISO/IEC 17025:2018 and, if applicable, additional legal and normative requirements, including those in relevant sectoral schemes, in order to carry out the conformity assessment activities listed below.

The management system requirements of DIN EN ISO/IEC 17025 are written in the language relevant to the operations of calibration laboratories and confirm generally with the principles of DIN EN ISO 9001.

Calibration in the fields:

Electrical quantities

High frequency quantities

- **HF impedance (reflection factor)**
- **HF attenuation**

This certificate annex is only valid together with the written accreditation certificate and reflects the status as indicated by the date of issue. The current status of any given scope of accreditation can be found in the directory of accredited bodies maintained by Deutsche Akkreditierungsstelle GmbH at <https://www.dakks.de>.

Permanent Laboratory

Calibration and Measurement Capabilities (CMC)				
Measurement quantity / Calibration item	Range	Measurement conditions / procedure	Expanded uncertainty of measurement	Remarks
HF-impedance (reflection factor) Magnitude	0 to 1	9 kHz to < 50 MHz 50 MHz to 2 GHz > 2 GHz to 8 GHz > 8 GHz to 12 GHz > 12 GHz to 18 GHz	0.0060 + 0.0090 · $ \Gamma ^2$ 0.0060 + 0.0060 · $ \Gamma ^2$ 0.0060 + 0.0075 · $ \Gamma ^2$ 0.0075 + 0.0095 · $ \Gamma ^2$ 0.0075 + 0.0105 · $ \Gamma ^2$	N-Connector 50 Ω Γ : reflection factor
HF-impedance (reflection factor) Magnitude	0 to 1	10 MHz to < 50 MHz 50 MHz to 8 GHz > 8 GHz to 18 GHz > 18 GHz to 20 GHz > 20 GHz to 26.5 GHz	0.0070 + 0.0190 · $ \Gamma ^2$ 0.0060 + 0.0080 · $ \Gamma ^2$ 0.0065 + 0.0090 · $ \Gamma ^2$ 0.0070 + 0.010 · $ \Gamma ^2$ 0.0100 + 0.011 · $ \Gamma ^2$	PC3.5-Connector Γ : reflection factor
HF-impedance (reflection factor) Magnitude	0 to 1	10 MHz to < 50 MHz 50 MHz to 4 GHz > 4 GHz to < 10 GHz 10 GHz to 16 GHz > 16 GHz to 20 GHz > 20 GHz to 40 GHz	0.0080 + 0.0210 · $ \Gamma ^2$ 0.0070 + 0.012 · $ \Gamma ^2$ 0.0100 + 0.010 · $ \Gamma ^2$ 0.0100 + 0.012 · $ \Gamma ^2$ 0.0110 + 0.012 · $ \Gamma ^2$ 0.0120 + 0.016 · $ \Gamma ^2$	PC 2.92-Connector Γ : reflection factor
HF-impedance (reflection factor) Magnitude	0 to 1	10 MHz to < 50 MHz 50 MHz to 2 GHz > 2 GHz to 4 GHz > 4 GHz to 8 GHz > 8 GHz to 12 GHz	0.0070 + 0.0065 · $ \Gamma ^2$ 0.0060 + 0.0065 · $ \Gamma ^2$ 0.0060 + 0.0075 · $ \Gamma ^2$ 0.0100 + 0.0095 · $ \Gamma ^2$ 0.0100 + 0.013 · $ \Gamma ^2$	N-Connector 75 Ω Γ : reflection factor

Permanent Laboratory

Calibration and Measurement Capabilities (CMC)				
Measurement quantity / Calibration item	Range	Measurement conditions / procedure	Expanded uncertainty of measurement	Remarks
HF-impedance (reflection factor) Magnitude	0 to 1	10 MHz to < 50 MHz 50 MHz to 4 GHz > 4 GHz to 8 GHz	0.0080 + 0.0070 · $ \Gamma ^2$ 0.0070 + 0.0070 · $ \Gamma ^2$ 0.0085 + 0.0095 · $ \Gamma ^2$	7/16-Connector Γ : reflection factor
HF-impedance (reflection factor) Phase angle φ	-180° to +180°	9 kHz to 40 GHz	$U(\varphi) = \arcsin\left(\frac{U(\Gamma)}{ \Gamma }\right) \cdot \frac{180^\circ}{\pi}$	All connector systems
HF-attenuation Magnitude	0 dB to 12 dB	9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.050 dB	N-Connector 50 Ω
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.050 dB	
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.065 dB	
	> 12 dB to 22 dB	9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.050 dB	
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.065 dB	
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.065 dB 0.055 dB 0.070 dB	
	> 22 dB to < 42 dB	9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.045 dB 0.030 dB 0.065 dB	
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.065 dB 0.055 dB 0.070 dB	
		9 kHz to < 1 MHz 1 MHz to 8,5 GHz > 8,5 GHz to 18 GHz	0.11 dB 0.060 dB 0.12 dB	
Phase angle φ	-180° to +180°	9 kHz to < 1 MHz 1 MHz to 8.5 GHz	0.50°	
		> 8,5 GHz to 18 GHz	0.45°	
		> 8,5 GHz to 18 GHz	1.0°	

Abbreviations used:

CMC Calibration and measurement capabilities
DIN German institute for standardization